

RF&WIFI Bulb



RF Control



WiFi Control



Feature

- One bulb can be controlled by different remotes
- Single color, Dual color, RGB or RGBW led bulbs for choose.
- Can be controlled by RF remote or Smart phone.
- Memory function

Parameter

Part No.	Input Voltage	LED Power	Color	Lamp Base	Max Diameter
SR-9601	86-265V	7W	Single Color	E27	60mm
SR-9602	86-265V	7W	WW+CW	E27	60mm
SR-9603	86-265V	7W	RGB	E27	60mm
SR-9604	86-265V	7W	RGBW	E27	60mm

Compatible with the RF remote below:

Single color Remote	SR-2819DIM, SR-2819SDIM, SR-2830A
Dual color Remote	SR-2819CCT, SR-2819SCCT, SR-2830B
RGB/RGBW remote	SR-2819, SR-2819T, SR-2819S, SR-2839, SR-2818, SR-2820,

Operation

For wall controller and remote controller:

Learning method 1:

- Make sure the correct connection between the bulb with power.
- Switch off the power, then switch on again, within 15 seconds immediately short press zone number twice, then long press zone number, the bulb blink means learnt successfully.

Deleting ID:

Switch off the power, then switch on again, long press on/off button on controller until bulb blink, means delete ID learned.

Learning method 2:

- Make sure the correct connection between the bulb with power.
- Switch on/off power 3 times, when bulb flash, immediately press zone number, then touch color wheel, the bulb blink means learnt successfully.

Deleting ID:

Switch on/off power 5 times, bulbs will blink which means delete successfully.

For APP:

Learning method 1:

Switch off the power, then switch on again, within 15 seconds, Selected any one room (there will be small tick on the upper right side), then touch color wheel, the bulb blinks means learnt successfully.

Learning method 2:

Enter into room editing interface, Switch off the power, then switch on again, within 15 seconds short press the learning button in room editing interface, select any one room, bulb blinks means learnt successfully.

Warranty Agreement

1) We provide lifelong technical assistance with this product:

- 5-year warranty. We print date on every products, for example :1125 means year 2011,week 25.The warranty is for free repair or replacement and covers manufacturing faults only.
- For faults beyond the 3-year warranty we reserve the right to charge for time and parts.

2) Limited Warrenty

- Any defects caused by wrong operation.
- Any damages caused by unauthorized removal, maintenance, modifying, incorrect connection and replacement of chips.
- Any damages due to transportation, vibration etc. after purchase.
- Any damages caused by earthquake, fire, lightning, pollution and abnormal voltage.
- Any damages caused by negligence, inappropriate storing at high temperatures and humidity or near harmful chemicals.
- Product has been updated

3) Repair or replacement as provided under this warranty is the exclusive remedy to the customer.

Safety & Warnings

1) The product shall be installed and serviced by a qualified person.

2) IP20.Please avoid the sun and rain. When installed outdoors, please ensure it is mounted in a water proof enclosure.

3) Always be sure to mount this unit in an area with proper ventilation to avoid overheating.

4) Please check if the output voltage of any LED power supplies used comply with the working voltage of the product.

5) Never connect any cables while power is on and always assure correct connections to avoid short circuits before switching on.

6) Please ensure that the cable is secured tightly in the connector

7) For update information please consult your supplier.